
COMPUTER SCIENCE**9608/32**

Paper 3 Written Paper

October/November 2018

MARK SCHEME

Maximum Mark: 75

Published

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge International will not enter into discussions about these mark schemes.

Cambridge International is publishing the mark schemes for the October/November 2018 series for most Cambridge IGCSE™, Cambridge International A and AS Level components and some Cambridge O Level components.

This document consists of **14** printed pages.

PUBLISHED**Generic Marking Principles**

These general marking principles must be applied by all examiners when marking candidate answers. They should be applied alongside the specific content of the mark scheme or generic level descriptors for a question. Each question paper and mark scheme will also comply with these marking principles.

GENERIC MARKING PRINCIPLE 1:

Marks must be awarded in line with:

- the specific content of the mark scheme or the generic level descriptors for the question
- the specific skills defined in the mark scheme or in the generic level descriptors for the question
- the standard of response required by a candidate as exemplified by the standardisation scripts.

GENERIC MARKING PRINCIPLE 2:

Marks awarded are always **whole marks** (not half marks, or other fractions).

GENERIC MARKING PRINCIPLE 3:

Marks must be awarded **positively**:

- marks are awarded for correct/valid answers, as defined in the mark scheme. However, credit is given for valid answers which go beyond the scope of the syllabus and mark scheme, referring to your Team Leader as appropriate
- marks are awarded when candidates clearly demonstrate what they know and can do
- marks are not deducted for errors
- marks are not deducted for omissions
- answers should only be judged on the quality of spelling, punctuation and grammar when these features are specifically assessed by the question as indicated by the mark scheme. The meaning, however, should be unambiguous.

GENERIC MARKING PRINCIPLE 4:

Rules must be applied consistently e.g. in situations where candidates have not followed instructions or in the application of generic level descriptors.

PUBLISHED**GENERIC MARKING PRINCIPLE 5:**

Marks should be awarded using the full range of marks defined in the mark scheme for the question (however; the use of the full mark range may be limited according to the quality of the candidate responses seen).

GENERIC MARKING PRINCIPLE 6:

Marks awarded are based solely on the requirements as defined in the mark scheme. Marks should not be awarded with grade thresholds or grade descriptors in mind.

PUBLISHED

Question	Answer	Marks
1(a)(i)	1 mark per bullet point: <ul style="list-style-type: none"> • Correct value for exponent identified e.g. (0.010101×2^5) • Used to give correct value e.g. 1010.1 or $21/64 \times 32$ • Correct answer i.e. 10.5 // $10\frac{1}{2}$ 	3
1(a)(ii)	1 mark per bullet point: <ul style="list-style-type: none"> • Correct binary value i.e. 111.1 • Value for exponent identified e.g. (0.1111×2^3) • Correct answer i.e. 01111000 00000011 	3
1(a)(iii)	1 mark per bullet point: <ul style="list-style-type: none"> • Any working method for conversion • Applied accurately • Correct answer i.e. 10001000 00000011 	3
1(b)(i)	<u>Largest</u> (positive) number (in this format)	1
1(b)(ii)	Overflow // too large to represent // would become negative	1

Question	Answer	Marks
2(a)	1 mark per bullet point to max 3: <ul style="list-style-type: none"> • Must have a <u>central</u> device • Each node is connected to the central device • Each node has a dedicated connection • Each connection must be bidirectional • Nodes may operate under different protocols 	3
2(b)(i)	1 mark per bullet point to max 2: <ul style="list-style-type: none"> • dedicated circuit/channel/(physical) path • connection established before/at the start of the communication • which lasts for duration of connection // circuit released at end of the communication • all data is transmitted along the same route 	2

PUBLISHED

Question	Answer	Marks															
2(b)(ii)	1 mark for each row: <table border="1" data-bbox="607 280 1666 608" style="margin-left: 40px;"> <thead> <tr> <th data-bbox="607 280 1039 344">Statements</th> <th data-bbox="1039 280 1359 344">Circuit switching</th> <th data-bbox="1359 280 1666 344">Packet switching</th> </tr> </thead> <tbody> <tr> <td data-bbox="607 344 1039 408">Shares bandwidth</td> <td data-bbox="1039 344 1359 408"></td> <td data-bbox="1359 344 1666 408">✓</td> </tr> <tr> <td data-bbox="607 408 1039 472">Data may arrive out of order</td> <td data-bbox="1039 408 1359 472"></td> <td data-bbox="1359 408 1666 472">✓</td> </tr> <tr> <td data-bbox="607 472 1039 536">Data can be corrupted</td> <td data-bbox="1039 472 1359 536">✓</td> <td data-bbox="1359 472 1666 536">✓</td> </tr> <tr> <td data-bbox="607 536 1039 608">Data are less likely to get lost</td> <td data-bbox="1039 536 1359 608">either✓</td> <td data-bbox="1359 536 1666 608">or✓</td> </tr> </tbody> </table>	Statements	Circuit switching	Packet switching	Shares bandwidth		✓	Data may arrive out of order		✓	Data can be corrupted	✓	✓	Data are less likely to get lost	either✓	or✓	4
Statements	Circuit switching	Packet switching															
Shares bandwidth		✓															
Data may arrive out of order		✓															
Data can be corrupted	✓	✓															
Data are less likely to get lost	either✓	or✓															


PUBLISHED

Question	Answer	Marks																						
3(a)	<p>1 mark per bullet point to max 3:</p> <ul style="list-style-type: none"> • Correct use of Idempotent law $Y = Y.Y$ $Y = Y + Y$ • Correct use of Complement law $0 = Y.\bar{Y}$ $1 = Y + \bar{Y}$ • Correct use of Distributive law $X(Y + Z) = X.Y + X.Z$ • Correct use of Redundancy law $X.\bar{Y} + Y = X + Y$ • Correct use of identity law $X.1 = X$ <p>1 mark for the correct answer</p> <p>For example:</p> <table style="width: 100%; border: none;"> <tr> <td style="width: 60%;">$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.C$</td> <td>Idempotent law</td> </tr> <tr> <td>$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.\bar{C} + A.B.C$</td> <td>Distributive law</td> </tr> <tr> <td>$X = A.\bar{C}.\bar{B} + A.B.\bar{C} + A.B.C$</td> <td>Complement/Inverse law</td> </tr> <tr> <td>$X = A.\bar{C} + A.B$</td> <td></td> </tr> <tr> <td>$X = A.\bar{C} + A.B$</td> <td>Correct answer</td> </tr> <tr> <td> </td> <td></td> </tr> <tr> <td>$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.C$</td> <td>Distributive law</td> </tr> <tr> <td>$X = A.\bar{C}.\bar{B} + A.B.C$</td> <td>Complement/Inverse law</td> </tr> <tr> <td>$X = A.\bar{C} + A.B.C$</td> <td></td> </tr> <tr> <td>$X = A.\bar{C} + A.B.C$</td> <td>Redundancy Law</td> </tr> <tr> <td>$X = A.\bar{C} + A.B$</td> <td>Correct answer</td> </tr> </table>	$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.C$	Idempotent law	$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.\bar{C} + A.B.C$	Distributive law	$X = A.\bar{C}.\bar{B} + A.B.\bar{C} + A.B.C$	Complement/Inverse law	$X = A.\bar{C} + A.B$		$X = A.\bar{C} + A.B$	Correct answer	 		$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.C$	Distributive law	$X = A.\bar{C}.\bar{B} + A.B.C$	Complement/Inverse law	$X = A.\bar{C} + A.B.C$		$X = A.\bar{C} + A.B.C$	Redundancy Law	$X = A.\bar{C} + A.B$	Correct answer	4
$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.C$	Idempotent law																							
$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.\bar{C} + A.B.C$	Distributive law																							
$X = A.\bar{C}.\bar{B} + A.B.\bar{C} + A.B.C$	Complement/Inverse law																							
$X = A.\bar{C} + A.B$																								
$X = A.\bar{C} + A.B$	Correct answer																							
$X = A.\bar{B}.\bar{C} + A.B.\bar{C} + A.B.C$	Distributive law																							
$X = A.\bar{C}.\bar{B} + A.B.C$	Complement/Inverse law																							
$X = A.\bar{C} + A.B.C$																								
$X = A.\bar{C} + A.B.C$	Redundancy Law																							
$X = A.\bar{C} + A.B$	Correct answer																							

Question	Answer	Marks																																				
3(b)(i)	<p>1 mark for first four as 0, 1 mark for 1011</p> <table border="1" data-bbox="342 284 730 874"> <thead> <tr> <th>A</th> <th>B</th> <th>C</th> <th>X</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>0</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>0</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>0</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>1</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>0</td></tr> <tr><td>1</td><td>1</td><td>0</td><td>1</td></tr> <tr><td>1</td><td>1</td><td>1</td><td>1</td></tr> </tbody> </table> <p style="margin-left: 350px;">} 1 mark</p> <p style="margin-left: 350px;">} 1 mark</p>	A	B	C	X	0	0	0	0	0	0	1	0	0	1	0	0	0	1	1	0	1	0	0	1	1	0	1	0	1	1	0	1	1	1	1	1	2
A	B	C	X																																			
0	0	0	0																																			
0	0	1	0																																			
0	1	0	0																																			
0	1	1	0																																			
1	0	0	1																																			
1	0	1	0																																			
1	1	0	1																																			
1	1	1	1																																			
3(b)(ii)	<p>1 mark for correct K-map</p> <table border="1" data-bbox="371 957 875 1249"> <thead> <tr> <th colspan="2"></th> <th colspan="4" style="text-align: center;">AB</th> </tr> <tr> <th colspan="2"></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> </thead> <tbody> <tr> <th rowspan="2" style="vertical-align: middle;">C</th> <th>0</th> <td>0</td> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <th>1</th> <td>0</td> <td>0</td> <td>1</td> <td>0</td> </tr> </tbody> </table>			AB						00	01	11	10	C	0	0	0	1	1	1	0	0	1	0	1													
		AB																																				
		00	01	11	10																																	
C	0	0	0	1	1																																	
	1	0	0	1	0																																	

Question	Answer	Marks																														
3(b)(iii)	<p>1 mark for each correct loop to max 2</p> <p style="text-align: center;">AB</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td></td> <td></td> <td style="text-align: center;">00</td> <td style="text-align: center;">01</td> <td style="text-align: center;">11</td> <td style="text-align: center;">10</td> </tr> <tr> <td style="text-align: center;">C</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">1</td> </tr> <tr> <td></td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> </tr> </table>			00	01	11	10	C	0	0	0	1	1		1	0	0	1	0	2												
		00	01	11	10																											
C	0	0	0	1	1																											
	1	0	0	1	0																											
3(b)(iv)	<p>1 mark per bullet point:</p> <ul style="list-style-type: none"> • $A\bar{C}$ • $+ A.B$ <p>$X = A\bar{C} + A.B$</p>	2																														
3(c)(i)	<p>1 mark per bullet point to max 2:</p> <ul style="list-style-type: none"> • Correct column headings and row headings – values only • Correct column headings and row headings – order <p>1 mark for 2 correct rows or columns, 2 marks for 4 correct rows or columns (based on headings)</p> <p style="text-align: center;">AB</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td></td> <td></td> <td style="text-align: center;">00</td> <td style="text-align: center;">01</td> <td style="text-align: center;">11</td> <td style="text-align: center;">10</td> </tr> <tr> <td style="text-align: center;">CD</td> <td style="text-align: center;">00</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> </tr> <tr> <td></td> <td style="text-align: center;">01</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> </tr> <tr> <td></td> <td style="text-align: center;">11</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> </tr> <tr> <td></td> <td style="text-align: center;">10</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> </tr> </table>			00	01	11	10	CD	00	0	1	1	0		01	0	0	1	0		11	0	0	1	0		10	0	0	1	0	4
		00	01	11	10																											
CD	00	0	1	1	0																											
	01	0	0	1	0																											
	11	0	0	1	0																											
	10	0	0	1	0																											

Question	Answer	Marks																																	
3(c)(ii)	1 mark for each correct loop to max 2: <table border="1" data-bbox="454 300 1021 678"><tr><td colspan="2"></td><td colspan="4" style="text-align: center;">AB</td></tr><tr><td colspan="2"></td><td style="text-align: center;">00</td><td style="text-align: center;">01</td><td style="text-align: center;">11</td><td style="text-align: center;">10</td></tr><tr><td rowspan="4" style="vertical-align: middle;">CD</td><td style="text-align: center;">00</td><td style="text-align: center;">0</td><td style="text-align: center;">1</td><td style="text-align: center;">1</td><td style="text-align: center;">0</td></tr><tr><td style="text-align: center;">01</td><td style="text-align: center;">0</td><td style="text-align: center;">0</td><td style="text-align: center;">1</td><td style="text-align: center;">0</td></tr><tr><td style="text-align: center;">11</td><td style="text-align: center;">0</td><td style="text-align: center;">0</td><td style="text-align: center;">1</td><td style="text-align: center;">0</td></tr><tr><td style="text-align: center;">10</td><td style="text-align: center;">0</td><td style="text-align: center;">0</td><td style="text-align: center;">1</td><td style="text-align: center;">0</td></tr></table>			AB						00	01	11	10	CD	00	0	1	1	0	01	0	0	1	0	11	0	0	1	0	10	0	0	1	0	2
		AB																																	
		00	01	11	10																														
CD	00	0	1	1	0																														
	01	0	0	1	0																														
	11	0	0	1	0																														
	10	0	0	1	0																														
3(c)(iii)	1 mark per bullet point: <ul style="list-style-type: none">• A.B• + B.C̄.D̄ X = A.B + B.C̄.D̄	2																																	

Question	Answer	Marks																				
4(a)	<p>1 mark per row</p> <table border="1" data-bbox="342 284 1205 743"> <thead> <tr> <th data-bbox="342 284 622 347" rowspan="2">Symbol</th> <th colspan="2" data-bbox="622 284 1205 347">Token</th> </tr> <tr> <th data-bbox="622 347 909 411">Value</th> <th data-bbox="909 347 1205 411">Type</th> </tr> </thead> <tbody> <tr> <td data-bbox="342 411 622 480">Number1</td> <td data-bbox="622 411 909 480">60</td> <td data-bbox="909 411 1205 480">Variable</td> </tr> <tr> <td data-bbox="342 480 622 549">Number2</td> <td data-bbox="622 480 909 549">61</td> <td data-bbox="909 480 1205 549">Variable</td> </tr> <tr> <td data-bbox="342 549 622 617">Answer</td> <td data-bbox="622 549 909 617">62</td> <td data-bbox="909 549 1205 617">Variable</td> </tr> <tr> <td data-bbox="342 617 622 686">10</td> <td data-bbox="622 617 909 686">63</td> <td data-bbox="909 617 1205 686">Constant//Literal</td> </tr> <tr> <td data-bbox="342 686 622 743">0</td> <td data-bbox="622 686 909 743">64</td> <td data-bbox="909 686 1205 743">Constant//Literal</td> </tr> </tbody> </table>	Symbol	Token		Value	Type	Number1	60	Variable	Number2	61	Variable	Answer	62	Variable	10	63	Constant//Literal	0	64	Constant//Literal	3
Symbol	Token																					
	Value	Type																				
Number1	60	Variable																				
Number2	61	Variable																				
Answer	62	Variable																				
10	63	Constant//Literal																				
0	64	Constant//Literal																				
4(b)	<p>1 mark for each circled section</p> 	2																				
4(c)(i)	(Code) Optimisation	1																				
4(c)(ii)	<p>1 mark per bullet point:</p> <ul style="list-style-type: none"> • LDD 236 • ADD 237 • ADD 238 • SUB 239 • STO 235 <p style="text-align: center;">Copy the instructions</p> <ul style="list-style-type: none"> • Remove line 4 STO 540 correct lines 3 and 6 in original code • Remove line 5 LDD 540 correct lines 3 and 6 in original code 	3																				

Question	Answer	Marks
4(c)(iii)	1 mark per bullet point: <ul style="list-style-type: none"> • Code has fewer instructions/occupies less space in memory • shortens execution time of program // time taken to execute whole program decreases 	2
4(d)	<p style="text-align: center;">1 mark ← 1 mark ← → 1 mark</p> <p>1 mark no operators on the stack anywhere</p>	4

PUBLISHED

Question	Answer	Marks																																																																					
5(a)	<p>1 mark per bullet point to max 4:</p> <ul style="list-style-type: none"> • RISC has fewer instructions // CISC has more instructions • RISC has many registers // CISC has few registers • RISCs instructions are simpler // CISC's instructions are more complex • RISC has a few instruction formats // CISC has many instruction formats • RISC usually uses single-cycle instructions // CISC uses multi-cycle instructions • RISC uses fixed-length instructions // CISC uses variable-length instructions • RISC has better pipelineability // CISC has poorer pipelineability • RISC requires less complex circuits // CISC requires more complex circuits • RISC has fewer addressing modes // CISC has more addressing modes • RISC makes more use of RAM // CISC makes more use of cache/less use of RAM • RISC has a hard-wired control unit // CISC has a programmable control unit • RISC only uses load and store instructions to address memory // CISC has many types of instructions to address memory 	4																																																																					
5(b)(i)	<p>1 mark per bullet point:</p> <ul style="list-style-type: none"> • Completing the As correctly • B in column 2, row 1 no other Bs in row 1 • Remainder correctly completed <table border="1" data-bbox="367 922 1906 1378" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th data-bbox="367 922 887 1054" rowspan="2">Stage</th> <th colspan="9" data-bbox="887 922 1906 986">Time interval</th> </tr> <tr> <th data-bbox="887 986 999 1054">1</th> <th data-bbox="999 986 1111 1054">2</th> <th data-bbox="1111 986 1223 1054">3</th> <th data-bbox="1223 986 1335 1054">4</th> <th data-bbox="1335 986 1447 1054">5</th> <th data-bbox="1447 986 1559 1054">6</th> <th data-bbox="1559 986 1671 1054">7</th> <th data-bbox="1671 986 1783 1054">8</th> <th data-bbox="1783 986 1906 1054">9</th> </tr> </thead> <tbody> <tr> <td data-bbox="367 1054 887 1118">Fetch instruction</td> <td data-bbox="887 1054 999 1118">A</td> <td data-bbox="999 1054 1111 1118">B</td> <td data-bbox="1111 1054 1223 1118">C</td> <td data-bbox="1223 1054 1335 1118">D</td> <td data-bbox="1335 1054 1447 1118"></td> <td data-bbox="1447 1054 1559 1118"></td> <td data-bbox="1559 1054 1671 1118"></td> <td data-bbox="1671 1054 1783 1118"></td> <td data-bbox="1783 1054 1906 1118"></td> </tr> <tr> <td data-bbox="367 1118 887 1182">Decode instruction</td> <td data-bbox="887 1118 999 1182"></td> <td data-bbox="999 1118 1111 1182">A</td> <td data-bbox="1111 1118 1223 1182">B</td> <td data-bbox="1223 1118 1335 1182">C</td> <td data-bbox="1335 1118 1447 1182">D</td> <td data-bbox="1447 1118 1559 1182"></td> <td data-bbox="1559 1118 1671 1182"></td> <td data-bbox="1671 1118 1783 1182"></td> <td data-bbox="1783 1118 1906 1182"></td> </tr> <tr> <td data-bbox="367 1182 887 1246">Execute instruction</td> <td data-bbox="887 1182 999 1246"></td> <td data-bbox="999 1182 1111 1246"></td> <td data-bbox="1111 1182 1223 1246">A</td> <td data-bbox="1223 1182 1335 1246">B</td> <td data-bbox="1335 1182 1447 1246">C</td> <td data-bbox="1447 1182 1559 1246">D</td> <td data-bbox="1559 1182 1671 1246"></td> <td data-bbox="1671 1182 1783 1246"></td> <td data-bbox="1783 1182 1906 1246"></td> </tr> <tr> <td data-bbox="367 1246 887 1310">Access operand in memory</td> <td data-bbox="887 1246 999 1310"></td> <td data-bbox="999 1246 1111 1310"></td> <td data-bbox="1111 1246 1223 1310"></td> <td data-bbox="1223 1246 1335 1310">A</td> <td data-bbox="1335 1246 1447 1310">B</td> <td data-bbox="1447 1246 1559 1310">C</td> <td data-bbox="1559 1246 1671 1310">D</td> <td data-bbox="1671 1246 1783 1310"></td> <td data-bbox="1783 1246 1906 1310"></td> </tr> <tr> <td data-bbox="367 1310 887 1374">Write result to register</td> <td data-bbox="887 1310 999 1374"></td> <td data-bbox="999 1310 1111 1374"></td> <td data-bbox="1111 1310 1223 1374"></td> <td data-bbox="1223 1310 1335 1374"></td> <td data-bbox="1335 1310 1447 1374">A</td> <td data-bbox="1447 1310 1559 1374">B</td> <td data-bbox="1559 1310 1671 1374">C</td> <td data-bbox="1671 1310 1783 1374">D</td> <td data-bbox="1783 1310 1906 1374"></td> </tr> </tbody> </table>	Stage	Time interval									1	2	3	4	5	6	7	8	9	Fetch instruction	A	B	C	D						Decode instruction		A	B	C	D					Execute instruction			A	B	C	D				Access operand in memory				A	B	C	D			Write result to register					A	B	C	D		3
Stage	Time interval																																																																						
	1	2	3	4	5	6	7	8	9																																																														
Fetch instruction	A	B	C	D																																																																			
Decode instruction		A	B	C	D																																																																		
Execute instruction			A	B	C	D																																																																	
Access operand in memory				A	B	C	D																																																																
Write result to register					A	B	C	D																																																															

Question	Answer	Marks																							
5(b)(ii)	1 mark per bullet point: <ul style="list-style-type: none"> • Correct number of cycles for pipelining 8 • Correct number of cycles without pipelining $4 \times 5 = 20$ • No of cycles saved $20 - 8 = 12$ 	3																							
5(c)	1 mark for each row <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th data-bbox="338 456 1079 595" rowspan="2" style="text-align: left; vertical-align: top;">Statement</th> <th colspan="3" data-bbox="1079 456 1424 523">Architecture</th> </tr> <tr> <th data-bbox="1079 523 1196 595" style="text-align: center;">SIMD</th> <th data-bbox="1196 523 1312 595" style="text-align: center;">MIMD</th> <th data-bbox="1312 523 1424 595" style="text-align: center;">SISD</th> </tr> </thead> <tbody> <tr> <td data-bbox="338 595 1079 671">Each processor executes a different instruction</td> <td data-bbox="1079 595 1196 671"></td> <td data-bbox="1196 595 1312 671" style="text-align: center;">✓</td> <td data-bbox="1312 595 1424 671"></td> </tr> <tr> <td data-bbox="338 671 1079 748">There is only one processor</td> <td data-bbox="1079 671 1196 748"></td> <td data-bbox="1196 671 1312 748"></td> <td data-bbox="1312 671 1424 748" style="text-align: center;">✓</td> </tr> <tr> <td data-bbox="338 748 1079 858">Each processor executes the same instruction input using data available in the dedicated memory</td> <td data-bbox="1079 748 1196 858" style="text-align: center;">✓</td> <td data-bbox="1196 748 1312 858"></td> <td data-bbox="1312 748 1424 858"></td> </tr> <tr> <td data-bbox="338 858 1079 959">Each processor typically has its own partition within a shared memory</td> <td data-bbox="1079 858 1196 959"></td> <td data-bbox="1196 858 1312 959" style="text-align: center;">✓</td> <td data-bbox="1312 858 1424 959"></td> </tr> </tbody> </table>	Statement	Architecture			SIMD	MIMD	SISD	Each processor executes a different instruction		✓		There is only one processor			✓	Each processor executes the same instruction input using data available in the dedicated memory	✓			Each processor typically has its own partition within a shared memory		✓		4
Statement	Architecture																								
	SIMD	MIMD	SISD																						
Each processor executes a different instruction		✓																							
There is only one processor			✓																						
Each processor executes the same instruction input using data available in the dedicated memory	✓																								
Each processor typically has its own partition within a shared memory		✓																							

PUBLISHED

Question	Answer	Marks															
6(a)	<p>1 mark for each term/description</p> <table border="1" data-bbox="342 284 1731 818"> <thead> <tr> <th data-bbox="342 284 421 352"></th> <th data-bbox="421 284 1335 352">Description</th> <th data-bbox="1335 284 1731 352">Term</th> </tr> </thead> <tbody> <tr> <td data-bbox="342 352 421 416">A</td> <td data-bbox="421 352 1335 416">The result of encryption that is transmitted to the recipient</td> <td data-bbox="1335 352 1731 416">Cipher text</td> </tr> <tr> <td data-bbox="342 416 421 520">B</td> <td data-bbox="421 416 1335 520">The type of cryptography where different keys are used, one for encryption and one for decryption.</td> <td data-bbox="1335 416 1731 520">Asymmetric or Public key</td> </tr> <tr> <td data-bbox="342 520 421 651">C</td> <td data-bbox="421 520 1335 651">Electronic document used to prove the ownership of a public key // Electronic document used to prove that the data is from a trusted source</td> <td data-bbox="1335 520 1731 651">Digital certificate</td> </tr> <tr> <td data-bbox="342 651 421 818">D</td> <td data-bbox="421 651 1335 818">Key needed to decrypt data that has been encrypted by a public key // Key needed to encrypt data so that it that can be decrypted by a public key // the key used in asymmetric encryption which is not shared</td> <td data-bbox="1335 651 1731 818">Private key</td> </tr> </tbody> </table>		Description	Term	A	The result of encryption that is transmitted to the recipient	Cipher text	B	The type of cryptography where different keys are used, one for encryption and one for decryption.	Asymmetric or Public key	C	Electronic document used to prove the ownership of a public key // Electronic document used to prove that the data is from a trusted source	Digital certificate	D	Key needed to decrypt data that has been encrypted by a public key // Key needed to encrypt data so that it that can be decrypted by a public key // the key used in asymmetric encryption which is not shared	Private key	4
	Description	Term															
A	The result of encryption that is transmitted to the recipient	Cipher text															
B	The type of cryptography where different keys are used, one for encryption and one for decryption.	Asymmetric or Public key															
C	Electronic document used to prove the ownership of a public key // Electronic document used to prove that the data is from a trusted source	Digital certificate															
D	Key needed to decrypt data that has been encrypted by a public key // Key needed to encrypt data so that it that can be decrypted by a public key // the key used in asymmetric encryption which is not shared	Private key															
6(b)	<p>1 mark for C in the correct place 1 mark for A followed by D in any position 1 mark for D followed by B in any position</p> <p>1 Browser requests that the server identifies itself 2 C 3 Browser checks the certificate against a list of trusted Certificate Authorities 4 A 5 D 6 B 7 Server and Browser now encrypt all transmitted data with the session key</p>	3															